

По вопросам продаж и поддержки обращайтесь:

Самары (7273)495-231
Самарск (3955)60-70-56
Архангельск (8182)63-90-72
Астрахань (8512)99-46-04
Барнаул (3852)73-04-60
Белгород (4722)40-23-64
Благовещенск (4162)22-76-07
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Владикавказ (8672)28-90-48
Владимир (4922)49-43-18
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89
Иваново (4932)77-34-06
Ижевск (3412)26-03-58
Иркутск (395)279-98-46
Казань (843)206-01-48

Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Коломна (4966)23-41-49
Кострома (4942)77-07-48
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курган (3522)50-90-47
Курск (4712)77-13-04
Липецк (4742)52-20-81
Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41
Нижний Новгород (831)429-08-12
Новокузнецк (3843)20-46-81
Новосибирск (383)227-86-73
Омск (3812)21-46-40
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16
Пермь (342)205-81-47
Петрозаводск (8142)55-98-37
Псков (8112)59-10-37
Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саранск (8342)22-96-24
Саратов (845)249-38-78
Севастополь (8692)22-31-93
Симферополь (3652)67-13-56
Смоленск (4812)29-41-54
Сочи (862)225-72-31
Ставрополь (8652)20-65-13
Сургут (3462)77-98-35

Сыктывкар (8212)25-95-17
Тамбов (4752)50-40-97
Тверь (4822)63-31-35
Тольятти (8482)63-91-07
Томск (3822)98-41-53
Тула (4872)33-79-87
Тюмень (3452)66-21-18
Улан-Удэ (3012)59-97-51
Ульяновск (8422)24-23-59
Уфа (347)229-48-12
Хабаровск (4212)92-98-04
Чебоксары (8352)28-53-07
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Чита (3022)38-34-83
Якутск (4112)23-90-97
Ярославль (4852)69-52-93

Россия +7(495)268-04-70

Казахстан +7(7172)727-132

Киргизия +996(312)96-26-47

<https://zebex.nt-rt.ru/> || zxb@nt-rt.ru

ТЕРМИНАЛЫ СБОРЫ ДАННЫХ

Технические характеристики на

МНОГОФУНКЦИОНАЛЬНЫЕ

СКАНЕРЫ

Z-7010, Z-7012, Z-7212



Z-7212 Android Fixed Computer

The all-new Z-7212 Android Fixed Computer is an “all in-one” solution that combines retail management, customer-centric multimedia, and integrated processing for POS or kiosk self-service applications.

The state-of-the-art kiosk provides exclusive features that optimize the user experience at every stage of interaction. The features include a high performance HD Capacitive type touch panel, IP54 protection, speaker output and microphone input, camera for face recognition, and PoE-enabled networking port.

- Embedded 1D/2D Image Barcode Scanner
- IP 54 Protection (with back cover installed)
- High power USB 2.0 port for external device
- Provide PoE DC power input method
- HDMI、RS232 Interface
- Low power consumption

SYSTEM	
CPU	TI OMAP 4470 Dual core 1.5GHz
Operating System	Android 4.2.2
Memory	1GB RAM & 16GB ROM
Display	10.1" 1280x800 IPS; Capacitive type 5 points touch
Scanner	1D/2D decoding capability
Audio	2 x 1W speaker 1 x microphones
Camera	Front : 5Mpixel 1080p 30fps capable imager
Keypad & Button	1. Power x 1 2. Volume (up and down)
I/O	HDMI x1; USB x 2 : --USB2.0 High Speed Type A (Host) port (current output up to 1.5A) --USB2.0 High Speed Type A (Host) port (current output up to 0.5A) MicroUSB x1 : MicroUSB2.0 High Speed Host + Client (OTG) port Audio in : External 3.5 mm port for external microphone Audio out : External 3.5 mm port for stereo analog audio out RS232 x 1;
Expansion Slot	64G SDXC Card expansion capability (FAT32 format)
RADIO COMMUNICATION	
WWLAN	Bluetooth V2.1 + EDR
WLAN	Dual Band (2.4 & 5GHz) 802.11 a / b / g / n
Ethernet	1 Giga Ethernet RJ45
POWER	
Input interface	1. POE input : IEEE 802.3af/at; Classification : 4 ;max. 25.5W. 2. AC adapter (Option) : Input : AC100~240C, 50~60 Hz ; Output : 12VDC / 4.16A
PHYSICAL	
Dimension	(L) 285mm x (W) 215.15mm x (H) 38.7mm
Weight	1340g
ENVIRONMENTAL	
Operating Temperature	0~50 °C
Storage Temperature	-20~70 °C
Humidity	20 ~ 90% RH (non-condensing)
Environmental Sealing	IP54 rated sealing (with back cover sealed)
REGULATORY	
Safety / EMC	CB, CE, FCC, NCC, BSMI
ACCESSORIES	
Option Accessory	Adapter(Input: AC100~240V, 50~60 Hz ; Output: 12VDC / 4.16A; Efficiency Level: VI)
Other	
Installation specification	Support VESA MIS-D 100 (100mm x 100mm)

Z-701x Series Windows CE.NET Fixed Computer

The Z-701x Series is the most powerful information kiosk with barcode scanner and user-friendly functionalities. It functions as a price checker in supermarket or a media player for promotional purpose. Available wall-mount kit makes it extremely versatile for all kinds of applications. PoE-enabled networking port allows an easy installation even without a power outlet nearby.

- 5.7" TFT VGA LCD with touch panel
- 520MHz, PXA270 CPU
- Optional 1D/2D/RFID scan engine & MSR expandable
- A PoE-enabled networking device
- Equipped with stereo speakers for multimedia purpose
- Easy-to-use and hassle-free installing design



MODEL	Z-7010 Series	Z-7012 Series
Input Device	1D laser or RFID module	2D image scan module
SYSTEM		
CPU	Marvell PXA270 520MHz processor	
Operating System	Microsoft® Windows® CE.NET 5.0	
Memory	128MB SDRAM / 2GB removable SD card	
Display	5.7" VGA (640 × 480 pixels) color transmissive TFT LCD with touch panel and LED back light	
Audio	Two stereo speakers	
Keypad & Button	5 buttons: HOME, ESC, Up/Right/Down/Left, ENT (Enter), FN input (Function)	
INTERFACE		
Ethernet	10/100 Mbps Ethernet (Supports PoE, IEEE 802.3af compliant)	
USB	USB version 1.1 Host for external device (back); USB version 1.1Client for external device (side)	
RS-232	Programmable up to 115,200 bps	
EXPANSION SLOT		
C/F Card Slot	Internal one compact flash Type II card slot (for data storage only)	
SD I/O Card Slot	One SD slot support up to 4GB	
POWER		
AC Adaptor	9VDC, 2A, 100V/240V input AC auto switching	
RADIO COMMUNICATION		
WLAN (Optional)	IEEE 802.11 b/g	
PHYSICAL		
Dimension	245.1 × 204.0 × 117.6 mm	
Weigh	Approx. 1,400 g	
ENVIRONMENTAL		
Operating Temperature	0°C – 50°C (32°F – 122°F)	
Storage Temperature	-10°C – 60°C (14°F – 140°F)	
Humidity	5% – 95% RH (non-condensing)	
REGULATORY		
Safety	LVD	
EMC	CE & FCC Part 15B	
ACCESSORY		
	AC adaptor 9VDC 2A, RS-232 cable, wall-mounting kit	

По вопросам продаж и поддержки обращайтесь:

Самары (7273)495-231
Саратов (3955)60-70-56
Архангельск (8182)63-90-72
Астрахань (8512)99-46-04
Барнаул (3852)73-04-60
Белгород (4722)40-23-64
Благовещенск (4162)22-76-07
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Владикавказ (8672)28-90-48
Владимир (4922)49-43-18
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89
Иваново (4932)77-34-06
Ижевск (3412)26-03-58
Иркутск (395)279-98-46
Казань (843)206-01-48

Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Коломна (4966)23-41-49
Кострома (4942)77-07-48
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курган (3522)50-90-47
Курск (4712)77-13-04
Липецк (4742)52-20-81
Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41
Нижний Новгород (831)429-08-12
Новокузнецк (3843)20-46-81
Новосибирск (383)227-86-73
Оябрьск(3496)41-32-12

Омск (3812)21-46-40
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16
Пермь (342)205-81-47
Петрозаводск (8142)55-98-37
Псков (8112)59-10-37
Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саранск (8342)22-96-24
Саратов (845)249-38-78
Севастополь (8692)22-31-93
Симферополь (3652)67-13-56
Смоленск (4812)29-41-54
Сочи (862)225-72-31
Ставрополь (8652)20-65-13
Сургут (3462)77-98-35

Сыктывкар (8212)25-95-17
Тамбов (4752)50-40-97
Тверь (4822)63-31-35
Тольятти (8482)63-91-07
Томск (3822)98-41-53
Тула (4872)33-79-87
Тюмень (3452)66-21-18
Улан-Удэ (3012)59-97-51
Ульяновск (8422)24-23-59
Уфа (347)229-48-12
Хабаровск (4212)92-98-04
Чебоксары (8352)28-53-07
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Чита (3022)38-34-83
Якутск (4112)23-90-97
Ярославль (4852)69-52-93

Россия +7(495)268-04-70

Казахстан +7(7172)727-132

Киргизия +996(312)96-26-47

<https://zebex.nt-rt.ru/> || zxb@nt-rt.ru